



ALPHA Series LLD Water-Cooled Gensets

LLD 95(A), LLD 135, LLD 140(A), LLD 190(A),
LLD 200, LLD 250(A), LLD 275, LLD 400

50 Hz; 1500/3000 r/min; power outputs: 5.9–43.5 kVA
60 Hz; 1800 r/min; power outputs: 7.3–25.3 kVA

Water-cooled mounted gensets with electronic control module

Choice of:

- ✓ 50 Hz, 1500/3000 r/min or 60 Hz, 1800 r/min
- ✓ Lister Petter ALPHA-Series water-cooled, direct injection diesel engine (two, three or four cylinders)
- ✓ naturally aspirated or turbocharged
- ✓ open set (LLD) or acoustic set (LLDA)

Standard Features

- control system with electronic digital control module (for features see page 3)
- single-bearing, 2 or 4-pole brushless alternator
- 66-litre polypropylene fuel tank with contents gauge
- galvanised steel base-plate with forklift pockets and bunding for the fuel tank
- anti-vibration mountings
- 12 V starter battery and leads
- mechanical governing
- emergency stop button (lock-down type)
- pusher fan
- Operators' Handbook
- electrical diagrams

Open Sets Only:

- engine-mounted exhaust silencer



Open Set (LLD)

Acoustic Sets Only:

- acoustic canopy
- residential exhaust silencer
- central point lifting eye
- external emergency stop button



Acoustic Set (LLDA)

ALPHA Series: LLD Water-Cooled Genset Technical Data Sheet

Power Outputs															
				50 Hz								60 Hz, 1800 r/min			
				1500 r/min				3000 r/min				1800 r/min			
				Single-Phase		Three-Phase		Single-Phase		Three-Phase		Single-Phase		Three-Phase	
				220V 230 V 240 V		380/220 V 400/230 V 415/240 V		220V 230 V 240 V		380/220 V 400/230 V 415/240 V		220 or 110 V 230 or 115 V 240 or 120 V		220/127	
Model	Engine	r/min	Rating	kVA	kW	kVA	kW	kVA	kW	kVA	kW	kVA	kW	kVA	kW
LLD 95(A)	LPW2	1500	Prime	5.9	5.9	7.7	6.2					kVA	kW	9.4	7.5
			Standby	6.5	6.5	8.5	6.8					8.1	8.1	10.3	8.3
LLD 135	LPW2	3000	Prime					10.2	10.2	13.7	11.0				
			Standby					11.2	11.2	15.1	12.1				
LLD 140(A)	LPW3	1500	Prime	9.1	9.1	11.9	9.5					11.0	11.0	14.7	11.7
			Standby	10.0	10.0	13.0	10.4					12.1	12.1	16.1	12.8
LLD 190(A)	LPW4	1500	Prime	12.0	12.0	16.0	12.8					15.3	15.3	17.5	14.0
			Standby	13.2	13.2	17.6	14.1					16.8	16.8	19.3	15.4
LLD 200	LPW3	3000	Prime					15.4	15.4	20.3	16.3				
			Standby					16.9	16.9	22.4	17.9				
LLD 250(A)	LPWT4	1500	Prime	15.4	15.4	20.0	16.0								
			Standby	17.0	17.0	22.0	17.6								
LLD 275	LPW4	3000	Prime					20.9	20.9	28.1	22.5				
			Standby					23.0	23.0	30.9	24.8				
LLD 400	LPWT4	3000	Prime							39.5	31.6				
			Standby							43.5	34.8				

Rating Definitions to ISO 8528-1

All ratings in the table are in accordance with ISO 8528-1.
Power Factor: Single phase, 1.0 pf; three-phase, 0.8 pf.
Voltages: Other voltages are available; refer to Lister Petter.

Power outputs are based on the optimum make of alternator for the set.
Gensets fitted with other manufacturers' alternators may not achieve the above ratings.

Rating Conditions

A standard generating set is designed to operate in environmental reference conditions of 25 °C, 100 kPa and 30% humidity.

Prime Power

This rating is for the supply of continuous electrical power (at variable load). There is no limit on the annual hours of operation and 10% overload power can be supplied for 1 hour in 12.

Standby Power

This rating is for the supply of continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted.

Optional Items:

- residential exhaust silencer for open sets (as fitted to acoustic)
- acoustic canopy kit (including residential silencer kit) for retro-fitting to electric-start open sets only
- 2-wheel trailer
- basic tool kit

Engine Accessories

- medium-duty air cleaner
- oil and fuel filters
- fuel-lift pump
- 12 V electric starting system

Alternator Specification

- single-bearing, 2 or 4-pole brushless alternator
- solid state AVR with $\pm 1.5\%$ voltage regulation as standard
- class "H" insulation on the rotor and stator
- IP23 protection class

Sound Pressure Levels ¹	
Engine	Acoustic sets, dBA, at 75% load at 7m
	50 Hz, 1500 r/min
LPW2	64
LPW3	64
LPW4	65
LPWT4	62

1. Noise levels are in accordance with European Noise Directive 2001/14/EC.

Control System Features

Control Cubicle

All LLD and LLDA sets have a control cubicle mounted on a vibration-isolated support, which has the following features:

- electronic digital control module with monitoring/control facility and warning indicators
- automatic shutdown protection
- emergency stop button (lock-down type)
- AC output circuit breaker with over-current protection
- DC circuit control switch and overload circuit breaker

The control module gives digital readouts of:

- generator voltage (phase-to-phase and phase-to-neutral)
- generator current (each phase displayed separately)
- output frequency
- engine speed
- engine oil pressure
- engine coolant temperature
- battery voltage
- engine hours run

The control module has indicators for:

- overspeed/underspeed
- emergency stop
- engine oil pressure
- engine temperature
- failure to start
- battery charger failure

Automatic shutdown occurs under:

- low engine oil pressure
- high engine temperature
- overspeed/underspeed
- failure to start after three attempts

Manual/Remote Start Sets

These sets have the flexibility of either manual or remote automatic operation:

- manual operation is by **START** and **STOP** push-buttons on the control module
- remote operation is achieved by connecting a 2-wire circuit to the relevant terminals on the control module and is activated by setting the control module to **AUTO**

Automatic Mains Failure Sets (AMF)

In the event of a mains failure, the generating set will automatically operate to supply the electrical load. In addition to the standard features, automatic mains failure sets have:

- wall-mounted cubicle governing automatic mains failure operation
- control module timer circuits set to delay start, delay transfer back to mains and delay stop to allow for engine cooldown
- solid-state automatic battery charger that maintains charge when set is not running

The wall-mounted cubicle features:

- mains monitoring unit to control set operation
- load-transfer contactors, mechanically and electrically interlocked (rated for set output)
- indicator for mains-on-load or plant-on-load

Approximate Fuel Consumption					
			Litres/Hour		
			50 Hz		60 Hz
Genset	Engine	Load	1500 r/min	3000 r/min	1800 r/min
LLD 95(A)	LPW2	100%	1.9		2.3
		75%	1.5		1.8
LLD 135	LPW2	100%		3.9	
		75%		3.1	
LLD 140(A)	LPW3	100%	2.8		3.4
		75%	2.2		2.7
LLD 190(A)	LPW4	100%	3.8		4.6
		75%	2.9		3.6
LLD 200	LPW3	100%		5.9	
		75%		4.6	
LLD 250(A)	LPWT4	100%	4.9		6.0
		75%	3.7		4.6
LLD 275	LPW4	100%		7.8	
		75%		6.1	
LLD 400	LPWT4	100%		10.6	
		75%		8.3	

ALPHA Series: LLD Water-Cooled Genset Technical Data Sheet

Approximate Dimensions			
	Open sets		
	Length (A)	mm	1442
		in	56.8
	Width (B)	mm	715
		in	28.1
	Height (C)	mm	997
in		39.25	
Acoustic sets			
Length (A)	mm	1693	
	in	66.6	
Width (B)	mm	743	
	in	29.2	
Height (C)	mm	1143	
	in	45.0	

Weight													
		Open Sets								Acoustic Sets			
		LLD 95	LLD 135	LLD 140	LLD 190	LLD 200	LLD 250	LLD 275	LLD 400	LLD 95A	LLD 140A	LLD 190A	LLD 250A
Dry weight	kg	396	396	417	456	417	466	456	466	500	540	580	590
	lb	873	873	919	1005	919	1027	1005	1027	1102	1190	1279	1301

A comprehensive range of options allows you to select a specification that matches your requirements. Please ask your Lister Petter distributor. (See panel below left.)

Distributor's Address



UK

Lister Petter Limited, Dursley, Gloucestershire
GL11 4HS England; Tel: +44 (0)1453 544141;

Fax: +44 (0)1453 546732;

E-mail: sales@lister-petter.co.uk <http://www.lister-petter.co.uk>

USA

Lister Petter Americas Inc. 815 E. 56 Highway, Olathe, Kansas 66061 USA

Tel: +1 913 764-3512; Fax: +1 913 764-5493;

E-mail: info@lister-petter.com; <http://www.lister-petter.com>

France

Lister Petter France, 17 Avenue de l'Escouvrier, Zone d'Activités,
95842 Sarcelles Cedex, France; Tel: +33 (0)1 39330420;

Fax: +33 (0)1 34195760; E-mail: commercial@lister-petter-france.fr

India

Lister Petter India (P) Limited, 32/2/5/1, Kondhawa (BK),
Pune 411048 India

Tel: +91 20 2693 2688/3644/3645; Fax: +91 20 2693 3286

Email: smith@listerpetterindia.com

China

Lister Petter China, Jinan Fuqiang Power Co. Ltd, Shandong Zhangqiu

Industrial Area, Jinan 250220, P.R. China

Tel: +86 531 8558 4852; Fax: +86 531 8558 4820

Lister Petter have made efforts to ensure that the information in this data sheet is accurate but reserve the right to amend specifications and information without notice and without obligation or liability.